

JUMPER	DMA1	DMA3	DISABLED
JE1	1-2	2-3	off (default)
JE2	1-2	2-3	off (default)

Table 2-2. SMC 665GT ECP Mode DMA Channel Selection

CPU Clock Jumper JK1-JK3

JUMPER	50 MHz	40 MHz	33.3 MHz	25 MHz
JK1	1-2	1-2	2-3 (default)	2-3
JK2	2-3	1-2	2-3 (default)	1-2
JK3	1-2	2-3	1-2 (default)	2-3

Table 2-3. CPU Clock Jumper Selection JK1-JK3

Connectors

The connectors allow the mainboard to connect electronically with other parts of the system. Some connectors have two pins, others have four or five pins. Some malfunction problems encountered with your system may be caused by loose or improper connections. Ensure that all connections are in place and firmly attached.

CONNECTOR	PIN-OUTS	SIGNAL NAME
CN1 PS/2 Keyboard Connector	1	Keyboard data
	2, 6	NC
	3	Ground
	4	+5V
	5	Keyboard clock
CN2 PS/2 Mouse Connector	1	Mouse data
	2	NC
	3, 6	Ground
	4	+ 5V
	5	Mouse clock

Table 2-4. Connector Pin Definitions (Continued)